

# Programming Instructions for Phone with Built-in [Hot Dialer](#)

Model 323-2GHQ



## Programming Instructions:

These instructions apply to all wall-mount or desk with built-in hot dialers. To program (or re-program) your Hot Dialer ( HD) phone, connect it to a phone line using the LINE socket, then call the phone from your cell phone or another landline phone (e.g. calling phone). When you here it ringing through your handset, wait 2 rings and then pick up the HD phone handset e.g. answer the call. At this time, enter the following sequence using the dialpad of the calling telephone keypad:

Step 1. **\*#1234** — wait to hear 'BEEP' — log in the system\*.

Step 2. **\*\*\*** — wait to hear 'BEEP' -- Set programming mode

Step 3. **\*\*9\*\*** — wait to hear 'BEEP' — wait to hear 'BEEP' — enters setup mode.

Step 4. **\*9\*1\*\*200\*NUMBER\*\*** — wait to hear 'BEEP' — enter hotline number.

Step 5. **\*\*235\*\*** — wait to hear 'BEEP' — enables auto dialing mode

Hang-up the calling phone. Done!

Note (1): This dialer accepts any string of numbers 0-9 and # (except \*).

Note (2): Wait 2 rings before answering the incoming call. Then, start dialing the digits (\*#1234) within 1 second after lifting up the handset.

Note (3): In case the above remote programming does not work, you may need to program your dialer locally. To do this, open the case, access the dialer, then connect the phone line in the LINE (black) jack and any handset on the TEL1 or TEL2. Then follow steps 2 to 5 above.

Note (4): NUMBER = The phone number you wish to program as the 'auto dial'.

Reset instructions: To reset the dialer to factory settings (e.g. removes the number to be dialed), you need to have a telephone with a dialpad connected to the TEL 1 or TEL2 sockets on the dialer. Then lift off the handset, wait 2 seconds (or until it finish dialing) and enter the following:

Step 1. **\*#1234** wait to hear 'BEEP' — log in the system.

Step 2. **\*\*9\*\*** Wait to hear 'BEEP' — resets dialer. Now you can re-program the hot dialer.

Hang-up the calling phone. Done!

For any additional question or if you need technical support programming or using your [hotline dialer](#), please visit [hqtelecom.com](http://hqtelecom.com)